arXiv:quant-ph/0307066v2 14 Jul 2003

N Level System with RWA and Analytical Solutions Revisited

Kazuyuki FUJII [*], Kyoko HIGASHIDA [†], Ryosuke KATO [‡], Yukako WADA [§]

Department of Mathematical Sciences

Yokohama City University

Yokohama, 236–0027

Japan

Abstract

In this paper we consider a model of an atom with n energy levels interacting with n(n-1)/2 external (laser) fields which is a natural extension of two level system, and assume the rotating wave approximation (RWA) from the beginning. We revisit some construction of analytical solutions (which correspond to Rabi oscillations) of the model in the general case and examine it in detail in the case of three level system.

[*]E-mail address : fujii@yokohama-cu.ac.jp

[†]E-mail address : s035577d@yokohama-cu.ac.jp

[‡]E-mail address : s035559g@yokohama-cu.ac.jp

[§]E-mail address : s035588a@yokohama-cu.ac.jp

1 Introduction

Our purpose of this paper is to apply a method developed in this one to Quantum Computation. Quantum Computation (or Computer) is a challenging task in this century for not only physicists but also mathematicians. See for example [1] as a general introduction.

Quantum Computation is in a usual understanding based on qubits which are based on two level system (two energy levels or fundamental spins of atoms), See [2], [3], [4], [5] as for general theory of two level system. In a realistic image of Quantum Computer we need at least one hundred atoms. However then we meet a very severe problem called Decoherence which will destroy a superposition of quantum states in the process of unitary evolution of our system. See for example [6] or recent [10] as an introduction. At the present it is not easy to control Decoherence.

By the way, an atom has in general infinitely many energy levels, while in a qubit method we use only two energy levels. We should use this possibility to reduce a number of atoms. We use n energy levels from the ground state (it is not realistic to take all energy levels into consideration at the same time). We call this n level system a qudit theory, see for example [14], [16], [19].

In a qubit case we need Rabi oscillations to construct quantum logic gates. See [12] as a simple introduction to quantum logic gates. Similarly we also need Rabi oscillations to construct them in a qudit space. However a general theory of Rabi oscillations in a n level system has not been developed enough as far as we know. For three level system see [3], [4] and [8]. Therefore we attempt such a theory in this paper.

In this model we assume the rotating wave approximation (RWA) from the beginning, otherwise we cannot solve the model. However there is no problem on the approximation in the weak coupling regime (the coupling constant is small enough compared to the energy differences of an atom). We note that there is a problem to use this approximation in the strong coupling regime.

Before stating our result let us make a review of Rabi oscillations (or coherent oscillations) in a two level system. For a quantum version of the Rabi oscillation see for

example, [5], [9], [13].

Let $\{\sigma_1, \sigma_2, \sigma_3\}$ be Pauli matrices :

$$\sigma_1 = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}, \quad \sigma_2 = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix}, \quad \sigma_3 = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}, \tag{1}$$

and we set

$$\sigma_+ = \frac{1}{2}(\sigma_1 + i\sigma_2) = \begin{pmatrix} 0 & 1 \\ 0 & 0 \end{pmatrix}, \quad \sigma_- = \frac{1}{2}(\sigma_1 - i\sigma_2) = \begin{pmatrix} 0 & 0 \\ 1 & 0 \end{pmatrix}.$$

Let us consider an atom with 2 energy levels E_0 and E_1 ($E_1 > E_0$). Its Hamiltonian is in the diagonal form given as

$$H_0 = \begin{pmatrix} E_0 & 0 \\ 0 & E_1 \end{pmatrix}. \tag{2}$$

This is rewritten as

$$H_0 = E_0 \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} + (E_1 - E_0) \begin{pmatrix} 0 & 0 \\ 0 & 1 \end{pmatrix} = E_0 \mathbf{1}_2 + \frac{\Delta}{2} (\mathbf{1}_2 - \sigma_3),$$

where $\Delta = E_1 - E_0$ is an energy difference. Since we usually take no interest in constant terms, we can set

$$H_0 = \frac{\Delta}{2} (\mathbf{1}_2 - \sigma_3). \tag{3}$$

We consider an atom with two energy levels which interacts with external (periodic) field with $g\cos(\omega t + \phi)$. In the following we set $\hbar = 1$ for simplicity. The Hamiltonian in the dipole approximation is given by

$$H = H_0 + g\cos(\omega t + \phi)\sigma_1 = \frac{\Delta}{2} (\mathbf{1}_2 - \sigma_3) + g\cos(\omega t + \phi)\sigma_1, \tag{4}$$

where ω is the frequency of the external field, g the coupling constant between the external field and the atom. This model is complicated enough, see [7], [11], [15], [17], [18].

In the following we set $\phi = 0$ for simplicity and assume the rotating wave approximation (which neglects the fast oscillating terms), namely

$$\cos(\omega t) = \frac{1}{2}(\mathrm{e}^{i\omega t} + \mathrm{e}^{-i\omega t}) = \frac{1}{2}\mathrm{e}^{i\omega t}(1 + \mathrm{e}^{-2i\omega t}) \approx \frac{1}{2}\mathrm{e}^{i\omega t},$$

and

$$\cos(\omega t)\sigma_1 = \begin{pmatrix} 0 & \cos(\omega t) \\ \cos(\omega t) & 0 \end{pmatrix} \approx \frac{1}{2}\begin{pmatrix} 0 & \mathrm{e}^{i\omega t} \\ \mathrm{e}^{-i\omega t} & 0 \end{pmatrix},$$

therefore the Hamiltonian is given by

$$H = \frac{\Delta}{2}\left(\mathbf{1}_2 - \sigma_3\right) + \frac{g}{2}\left(\mathrm{e}^{i\omega t}\sigma_+ + \mathrm{e}^{-i\omega t}\sigma_-\right) \equiv \frac{\Delta}{2}\left(\mathbf{1}_2 - \sigma_3\right) + g\left(\mathrm{e}^{i\omega t}\sigma_+ + \mathrm{e}^{-i\omega t}\sigma_-\right) \tag{5}$$

by the redefinition of g ($g/2 \longrightarrow g$). It is explicitly

$$H = \begin{pmatrix} 0 & g\mathrm{e}^{i\omega t} \\ g\mathrm{e}^{-i\omega t} & \Delta \end{pmatrix}. \tag{6}$$

We would like to solve the Schrödinger equation

$$i\frac{d}{dt}\Psi = H\Psi. \tag{7}$$

For that let us decompose H in (6) into

$$\begin{pmatrix} 0 & g\mathrm{e}^{i\omega t} \\ g\mathrm{e}^{-i\omega t} & \Delta \end{pmatrix} = \begin{pmatrix} 1 & \\ & \mathrm{e}^{-i\omega t} \end{pmatrix}\begin{pmatrix} 0 & g \\ g & \Delta \end{pmatrix}\begin{pmatrix} 1 & \\ & \mathrm{e}^{i\omega t} \end{pmatrix}, \tag{8}$$

so if we set

$$\Phi = \begin{pmatrix} 1 & \\ & \mathrm{e}^{i\omega t} \end{pmatrix}\Psi \quad \Longleftrightarrow \quad \Psi = \begin{pmatrix} 1 & \\ & \mathrm{e}^{-i\omega t} \end{pmatrix}\Phi \tag{9}$$

then it is not difficult to see

$$i\frac{d}{dt}\Phi = \begin{pmatrix} 0 & g \\ g & \Delta - \omega \end{pmatrix}\Phi, \tag{10}$$

which is easily solved. For simplicity we set the resonance condition

$$\Delta = \omega, \tag{11}$$

then the solution of (10) is

$$\Phi(t) = \exp\left\{-igt\begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}\right\}\Phi(0) = \begin{pmatrix} \cos(gt) & -i\sin(gt) \\ -i\sin(gt) & \cos(gt) \end{pmatrix}\Phi(0).$$

As a result, the solution of the equation (7) is given as

$$\Psi(t) = \begin{pmatrix} 1 & \\ & \mathrm{e}^{-i\omega t} \end{pmatrix} \Phi(t) = \begin{pmatrix} 1 & \\ & \mathrm{e}^{-i\omega t} \end{pmatrix} \begin{pmatrix} \cos(gt) & -i\sin(gt) \\ -i\sin(gt) & \cos(gt) \end{pmatrix} \Phi(0) \tag{12}$$

by (9). If we choose $\Phi(0) = (1,\ 0)^T$ as an initial condition, then

$$\Psi(t) = \begin{pmatrix} \cos(gt) \\ -i\mathrm{e}^{-i\omega t}\sin(gt) \end{pmatrix}. \tag{13}$$

This is a well–known model of the Rabi oscillation (or coherent oscillation).

2 N Level System $\cdots$ General Theory

In general, an atom has an infinitely many energy levels, however it is not realistic to consider all of them at the same time. Therefore we take only n energy levels from the ground state into consideration ($E_{n-1} > \cdots > E_1 > E_0$). Then from the lesson in the preceding section the energy Hamiltonian can be written as

$$H_0 = \begin{pmatrix} 0 & & & & & \\ & \Delta_1 & & & & \\ & & \Delta_2 & & & \\ & & & \cdot & & \\ & & & & \cdot & \\ & & & & & \Delta_{n-1} \end{pmatrix}, \tag{14}$$

where $\Delta_j = E_j - E_0$ for $1 \leq j \leq n-1$. For this atom we consider the interaction with $n(n-1)/2$ independent external (laser) fields corresponding to every energy difference ($E_j - E_i$ for $j > i$). Then the interaction term assuming the RWA from the beginning is

given as

$$V = \begin{pmatrix} 0 & \mathrm{e}^{i\omega_{01}t} & \mathrm{e}^{i\omega_{02}t} & . & . & . & \mathrm{e}^{i\omega_{0,n-1}t} \\ \mathrm{e}^{-i\omega_{01}t} & 0 & \mathrm{e}^{i\omega_{12}t} & . & . & . & \mathrm{e}^{i\omega_{1,n-1}t} \\ \mathrm{e}^{-i\omega_{02}t} & \mathrm{e}^{-i\omega_{12}t} & 0 & . & . & . & \mathrm{e}^{i\omega_{2,n-1}t} \\ . & . & . & . & . & . & . \\ . & . & . & . & . & . & . \\ . & . & . & . & . & 0 & \mathrm{e}^{i\omega_{n-2,n-1}t} \\ \mathrm{e}^{-i\omega_{0,n-1}t} & \mathrm{e}^{-i\omega_{1,n-1}t} & \mathrm{e}^{-i\omega_{2,n-1}t} & . & . & \mathrm{e}^{-i\omega_{n-2,n-1}t} & 0 \end{pmatrix}, \tag{15}$$

so the full Hamiltonian is

$$H = H_0 + gV, \tag{16}$$

where g is the coupling constant. Here we set

$$\omega_1 = \omega_{01},\ \omega_2 = \omega_{12},\ \cdots,\ \omega_{n-2} = \omega_{n-3,n-2},\ \omega_{n-1} = \omega_{n-2,n-1}$$

for simplicity. We would like to solve the Schrödinger equation

$$i\frac{d}{dt}\Psi = H\Psi. \tag{17}$$

Similarly in (8) let us decompose H : For

$$U = \begin{pmatrix} 1 & & & & & & \\ & \mathrm{e}^{i\omega_1 t} & & & & & \\ & & \mathrm{e}^{i(\omega_1+\omega_2)t} & & & & \\ & & & . & & & \\ & & & & . & & \\ & & & & & \mathrm{e}^{i(\omega_1+\omega_2+\cdots+\omega_{n-2})t} & \\ & & & & & & \mathrm{e}^{i(\omega_1+\omega_2+\cdots+\omega_{n-1})t} \end{pmatrix} \tag{18}$$

it is easy to see

$$H_U \equiv U^\dagger H U = \begin{pmatrix} 0 & g & g\mathrm{e}^{i\epsilon_{02}t} & \cdot & \cdot & g\mathrm{e}^{i\epsilon_{0,n-2}t} & g\mathrm{e}^{i\epsilon_{0,n-1}t} \\ g & \Delta_1 & g & \cdot & \cdot & g\mathrm{e}^{i\epsilon_{1,n-2}t} & g\mathrm{e}^{i\epsilon_{1,n-1}t} \\ g\mathrm{e}^{-i\epsilon_{02}t} & g & \Delta_2 & \cdot & \cdot & g\mathrm{e}^{i\epsilon_{2,n-2}t} & g\mathrm{e}^{i\epsilon_{2,n-1}t} \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ g\mathrm{e}^{-i\epsilon_{0,n-2}t} & g\mathrm{e}^{-i\epsilon_{1,n-2}t} & g\mathrm{e}^{-i\epsilon_{2,n-2}t} & \cdot & \cdot & \Delta_{n-2} & g \\ g\mathrm{e}^{-i\epsilon_{0,n-1}t} & g\mathrm{e}^{-i\epsilon_{1,n-1}t} & g\mathrm{e}^{-i\epsilon_{2,n-1}t} & \cdot & \cdot & g & \Delta_{n-1} \end{pmatrix}, \tag{19}$$

where

$$\epsilon_{ij} = \omega_{ij} - (\omega_{i+1} + \omega_{i+2} + \cdots + \omega_j)$$

for $j - i \geq 2$.

By setting

$$\tilde{\Psi} = U\Psi \iff \Psi = U^\dagger \tilde{\Psi}$$

it is not difficult to see

$$i\frac{d}{dt}\tilde{\Psi} = \tilde{H}_U \tilde{\Psi}, \tag{20}$$

where

$$\tilde{H}_U = \begin{pmatrix} 0 & g & g\mathrm{e}^{i\epsilon_{02}t} & \cdot & \cdot & g\mathrm{e}^{i\epsilon_{0,n-2}t} & g\mathrm{e}^{i\epsilon_{0,n-1}t} \\ g & \Delta_1 - \omega_1 & g & \cdot & \cdot & g\mathrm{e}^{i\epsilon_{1,n-2}t} & g\mathrm{e}^{i\epsilon_{1,n-1}t} \\ g\mathrm{e}^{-i\epsilon_{02}t} & g & \Delta_2 - (\omega_1+\omega_2) & \cdot & \cdot & g\mathrm{e}^{i\epsilon_{2,n-2}t} & g\mathrm{e}^{i\epsilon_{2,n-1}t} \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ g\mathrm{e}^{-i\epsilon_{0,n-2}t} & g\mathrm{e}^{-i\epsilon_{1,n-2}t} & g\mathrm{e}^{-i\epsilon_{2,n-2}t} & \cdot & \cdot & \Delta_{n-2} - \sum_{l=1}^{n-2}\omega_l & g \\ g\mathrm{e}^{-i\epsilon_{0,n-1}t} & g\mathrm{e}^{-i\epsilon_{1,n-1}t} & g\mathrm{e}^{-i\epsilon_{2,n-1}t} & \cdot & \cdot & g & \Delta_{n-1} - \sum_{l=1}^{n-1}\omega_l \end{pmatrix}. \tag{21}$$

At this stage we set the resonance conditions

$$\begin{aligned} &\Delta_1 = \omega_1,\ \Delta_2 = \omega_1 + \omega_2,\ \cdots,\ \Delta_{n-2} = \sum_{l=1}^{n-2} \omega_l,\ \Delta_{n-1} = \sum_{l=1}^{n-1} \omega_l \\ \Longleftrightarrow\ &\omega_j = E_j - E_{j-1}\ (j = 1,\ 2,\ \cdots,\ n-1) \end{aligned} \tag{22}$$

to make the situation simpler. Therefore $\tilde{H}_U$ can be written as

$$\tilde{H}_U = gC + gR,$$

where

$$C = \begin{pmatrix} 0 & 1 & & & & & \\ 1 & 0 & 1 & & & & \\ & 1 & 0 & 1 & & & \\ & & . & . & . & & \\ & & & . & . & . & \\ & & & & 1 & 0 & 1 \\ & & & & & 1 & 0 \end{pmatrix} \tag{23}$$

and

$$R(t) = \begin{pmatrix} 0 & 0 & e^{i\epsilon_{02}t} & . & . & e^{i\epsilon_{0,n-2}t} & e^{i\epsilon_{0,n-1}t} \\ 0 & 0 & 0 & . & . & e^{i\epsilon_{1,n-2}t} & e^{i\epsilon_{1,n-1}t} \\ e^{-i\epsilon_{02}t} & 0 & 0 & . & . & e^{i\epsilon_{2,n-2}t} & e^{i\epsilon_{2,n-1}t} \\ . & . & . & . & . & . & . \\ . & . & . & . & . & . & . \\ e^{-i\epsilon_{0,n-2}t} & e^{-i\epsilon_{1,n-2}t} & e^{-i\epsilon_{2,n-2}t} & . & . & 0 & 0 \\ e^{-i\epsilon_{0,n-1}t} & e^{-i\epsilon_{1,n-1}t} & e^{-i\epsilon_{2,n-1}t} & . & . & 0 & 0 \end{pmatrix}. \tag{24}$$

Therefore the Schrödinger equation becomes

$$i\frac{d}{dt}\tilde{\Psi} = (gC + gR)\tilde{\Psi}. \tag{25}$$

Now it is easy to solve

$$i\frac{d}{dt}\tilde{\Psi} = gC\tilde{\Psi},$$

which solution is

$$\tilde{\Psi}(t) = \exp(-igtC)\tilde{\Psi}(0).$$

By making use of the method of constant variation

$$\tilde{\Psi}(t) = \exp(-igtC)\tilde{\Psi}(0) \longrightarrow \tilde{\Psi}(t) = \exp(-igtC)\phi(t)$$

and substituting this into (25) we have the equation

$$i\frac{d}{dt}\phi = g\exp(igtC)R(t)\exp(-igtC)\phi \equiv gA(t)\phi, \quad \text{where} \tag{26}$$

$$A(t) = \exp(igtC)R(t)\exp(-igtC). \tag{27}$$

For this equation a formal solution called the Dyson series[1] has been known

$$\begin{aligned}\phi(t) &= :\exp\left(-ig\int_0^t A(s)ds\right):\phi(0) \\ &\equiv \left[\mathbf{1} - ig\int_0^t A(s)ds - g^2\int_0^t \left\{A(s)\int_0^s A(u)du\right\}ds + \cdots\right]\phi(0).\end{aligned} \tag{28}$$

However it is usually almost impossible to perform integrals. Anyway, our formal solution of the equation (20) becomes

$$\tilde{\Psi}(t) = \exp(-igtC) :\exp\left(-ig\int_0^t A(s)ds\right): \Psi \tag{29}$$

where Ψ is a constant vector. As a conclusion, a formal solution of (17) is given by

$$\Psi(t) = U(t)^\dagger\tilde{\Psi}(t) = U(t)^\dagger\exp(-igtC) :\exp\left(-ig\int_0^t A(s)ds\right): \Psi \tag{30}$$

with $U(t)$ in (18).

Lastly let us calculate $\exp(-igtC)$ in (30). For that purpose we need to make C in (23) a diagonal form. First let us calculate eigenvalues. The characteristic equation of C is

$$f_n(\lambda) \equiv \begin{vmatrix} \lambda & -1 & & & & & \\ -1 & \lambda & -1 & & & & \\ & -1 & \lambda & -1 & & & \\ & & \cdot & \cdot & \cdot & & \\ & & & \cdot & \cdot & \cdot & \\ & & & & -1 & \lambda & -1 \\ & & & & & -1 & \lambda \end{vmatrix} = 0. \tag{31}$$

[1] In Mathematics it was called the Peano series a long time ago, [20]

By the Laplace expansion with respect to the first column we have a recurrent equation

$$f_n(\lambda) = \lambda f_{n-1}(\lambda) - f_{n-2}(\lambda) \quad \text{and} \quad f_2(\lambda) = \lambda^2 - 1,\ f_3(\lambda) = \lambda^3 - 2\lambda. \tag{32}$$

For example, $f_4(\lambda) = \lambda^4 - 3\lambda^2 + 1$. From these equations it is not easy to conjecture the eigenvalues. However we know a good method ! We set

$$\lambda = x + \frac{1}{x} = x + x^{-1}. \tag{33}$$

Then for example,

$$f_2(x) = x^2 + 1 + x^{-2},\ f_3(x) = x^3 + x^1 + x^{-1} + x^{-3},\ f_4(x) = x^4 + x^2 + 1 + x^{-2} + x^{-4}.$$

In general

$$f_n(x) = \sum_{j=0}^{n} x^{-n+2j} = x^{-n}\frac{x^{2n+2} - 1}{x^2 - 1}. \tag{34}$$

The solutions of $f_n(x) = 0$ are $\{\exp(\sqrt{-1}\pi j/(n+1)) \mid j = 1, 2, \cdots, n, n+2, \cdots, 2n+1\}$ ($\sqrt{-1} = i$) because $x \neq \pm 1$. Therefore our solutions are

$$\lambda_j = x_j + x_j^{-1} = 2\cos\left(\frac{\pi j}{n+1}\right) \quad \text{for} \quad j = 1, 2, \cdots, n \tag{35}$$

by removing the overlap.

Next let us calculate an eigenfunction corresponding to λ_j

$$C|j\rangle = \lambda_j|j\rangle = 2\cos\left(\frac{\pi j}{n+1}\right)|j\rangle$$

for $j = 1, 2, \cdots, n$. If we define

$$|j\rangle = \sqrt{\frac{2}{n+1}}\left(\sin\left(\frac{\pi j}{n+1}\right), \sin\left(\frac{\pi 2j}{n+1}\right), \cdots, \sin\left(\frac{\pi kj}{n+1}\right), \cdots, \sin\left(\frac{\pi nj}{n+1}\right)\right)^T, \tag{36}$$

then it is not difficult to see

$$C|j\rangle = 2\cos\left(\frac{\pi j}{n+1}\right)|j\rangle \quad \text{and} \quad \langle j|k\rangle = \delta_{jk}. \tag{37}$$

We leave the proof to the readers. Now we define

$$O = (O_{jk}) \quad \text{where} \quad O_{jk} = \sqrt{\frac{2}{n+1}}\sin\left(\frac{\pi jk}{n+1}\right) \quad \Longrightarrow \quad OO^T = \mathbf{1}_n \tag{38}$$

and

$$D = (D_{jk}) \quad \text{where} \quad D_{jk} = 2\cos\left(\frac{\pi j}{n+1}\right)\delta_{jk}, \tag{39}$$

then we can diagonalize C like

$$C = ODO^T. \tag{40}$$

Therefore we finally obtain

$$\exp(-igtC) = O\exp(-igtD)O^T \tag{41}$$

or in components

$$\exp(-igtC)_{jk} = \frac{2}{n+1}\sum_{l=1}^{n}\exp\left(-2igt\cos\left(\frac{\pi l}{n+1}\right)\right)\sin\left(\frac{\pi jl}{n+1}\right)\sin\left(\frac{\pi kl}{n+1}\right). \tag{42}$$

In the case of $n = 3$ let us write down $\exp(-igtC)$ explicitly for the sake of latter convenience.

$$\exp(-igtC) = \frac{1}{2}\begin{pmatrix} 1+\cos(\sqrt{2}gt) & -i\sqrt{2}\sin(\sqrt{2}gt) & -1+\cos(\sqrt{2}gt) \\ -i\sqrt{2}\sin(\sqrt{2}gt) & 2\cos(\sqrt{2}gt) & -i\sqrt{2}\sin(\sqrt{2}gt) \\ -1+\cos(\sqrt{2}gt) & -i\sqrt{2}\sin(\sqrt{2}gt) & 1+\cos(\sqrt{2}gt) \end{pmatrix}. \tag{43}$$

For (41) with (42) we would like to calculate the Dyson series (28). However it is almost impossible in the general case, so in the last section we calculate the next–leading term in the case of $n = 3$ by making use of (43).

3 N Level System $\cdots$ An Exact Solution

In this section we present an exact solution in the general case under some "consistency condition" (in our terminology).

In section 2 we consider a very special case : namely, in (24) we take

$$\epsilon_{ij} = \omega_{ij} - (\omega_{i+1} + \omega_{i+2} + \cdots + \omega_j) = 0 \tag{44}$$

for all $j - i \geq 2$. We call this a consistency condition. Then $\tilde{H}_U$ becomes a constant matrix !

$$\tilde{H}_U = gC + gR = g \begin{pmatrix} 0 & 1 & 1 & \cdot & \cdot & 1 & 1 \\ 1 & 0 & 1 & \cdot & \cdot & 1 & 1 \\ 1 & 1 & 0 & \cdot & \cdot & 1 & 1 \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ \cdot & \cdot & \cdot & \cdot & \cdot & \cdot & \cdot \\ 1 & 1 & 1 & \cdot & \cdot & 0 & 1 \\ 1 & 1 & 1 & \cdot & \cdot & 1 & 0 \end{pmatrix} \equiv gQ, \tag{45}$$

so it is easy to solve the equation (25)

$$i\frac{d}{dt}\tilde{\Psi} = g(C + R)\tilde{\Psi} = gQ\tilde{\Psi}.$$

The solution is formally

$$\tilde{\Psi}(t) = \exp(-igtQ)\tilde{\Psi}(0).$$

Let us calculate $\exp(-igtQ)$ explicitly. If we define

$$|\mathbf{1}\rangle = (1, 1, \cdots, 1, 1)^T,$$

then it is easy to see $Q = |\mathbf{1}\rangle\langle\mathbf{1}| - \mathbf{1}_n$, so

$$\tilde{\Psi}(t) = e^{igt}\exp(-igt|\mathbf{1}\rangle\langle\mathbf{1}|)\tilde{\Psi}(0).$$

Since $\langle\mathbf{1}|\mathbf{1}\rangle = n$,

$$(|\mathbf{1}\rangle\langle\mathbf{1}|)^k = n^{k-1}|\mathbf{1}\rangle\langle\mathbf{1}|,$$

so that

$$\begin{aligned} \exp(-igt|\mathbf{1}\rangle\langle\mathbf{1}|) &= \mathbf{1}_n + \sum_{k=1}^{\infty} \frac{(-igt)^k}{k!} (|\mathbf{1}\rangle\langle\mathbf{1}|)^k = \mathbf{1}_n + \sum_{k=1}^{\infty} \frac{(-igt)^k}{k!} n^{k-1}|\mathbf{1}\rangle\langle\mathbf{1}| \\ &= \mathbf{1}_n + \frac{1}{n}\left\{\sum_{k=0}^{\infty} \frac{(-ingt)^k}{k!} - 1\right\}|\mathbf{1}\rangle\langle\mathbf{1}| = \mathbf{1}_n + \frac{\exp(-ingt) - 1}{n}|\mathbf{1}\rangle\langle\mathbf{1}|. \end{aligned} \tag{46}$$

Therefore we obtain

$$\tilde{\Psi}(t) = e^{igt}\left\{\mathbf{1}_n + \frac{\exp(-ingt)-1}{n}|\mathbf{1}\rangle\langle\mathbf{1}|\right\}\tilde{\Psi}(0). \tag{47}$$

Here if we choose $\tilde{\Psi}(0) = (1, 0, \cdots, 0, 0)^T = |0\rangle$, then

$$\tilde{\Psi}(t) = e^{igt}\left\{|0\rangle + \frac{\exp(-ingt)-1}{n}|\mathbf{1}\rangle\right\}.$$

As a result, the solution that is looking for is just

$$\Psi(t) = e^{igt}U(t)^\dagger\left\{|0\rangle + \frac{\exp(-ingt)-1}{n}|\mathbf{1}\rangle\right\} \tag{48}$$

with (18). In particular, in the case of $n = 3$ the solution is

$$\begin{aligned}\Psi(t) &= e^{igt}\begin{pmatrix} 1 & & \\ & \mathrm{e}^{-i\omega_1 t} & \\ & & \mathrm{e}^{-i(\omega_1+\omega_2)t}\end{pmatrix}\begin{pmatrix} \frac{\exp(-i3gt)+2}{3} \\ \frac{\exp(-i3gt)-1}{3} \\ \frac{\exp(-i3gt)-1}{3}\end{pmatrix} \\ &= \begin{pmatrix} e^{igt}\frac{\exp(-i3gt)+2}{3} \\ e^{i(g-\omega_1)t}\frac{\exp(-i3gt)-1}{3} \\ e^{i(g-\omega_1-\omega_2)t}\frac{\exp(-i3gt)-1}{3}\end{pmatrix}.\end{aligned} \tag{49}$$

4 Three Level System $\cdots$ An Approximate Solution

We calculate the case of $n = 3$ in more detail. For that purpose let us list $U(t)^\dagger$, $\exp(-igtC)$ and $R(t)$ once more :

$$U(t)^\dagger = \begin{pmatrix} 1 & & \\ & \mathrm{e}^{-i\omega_1 t} & \\ & & \mathrm{e}^{-i(\omega_1+\omega_2)t}\end{pmatrix}$$

and

$$\exp(-igtC) = \frac{1}{2}\begin{pmatrix} 1+\cos(\sqrt{2}gt) & -i\sqrt{2}\sin(\sqrt{2}gt) & -1+\cos(\sqrt{2}gt) \\ -i\sqrt{2}\sin(\sqrt{2}gt) & 2\cos(\sqrt{2}gt) & -i\sqrt{2}\sin(\sqrt{2}gt) \\ -1+\cos(\sqrt{2}gt) & -i\sqrt{2}\sin(\sqrt{2}gt) & 1+\cos(\sqrt{2}gt)\end{pmatrix}$$

and

$$R(t) = \begin{pmatrix} 0 & 0 & \exp(i\epsilon t) \\ 0 & 0 & 0 \\ \exp(-i\epsilon t) & 0 & 0 \end{pmatrix}$$

where $\epsilon \equiv \epsilon_{02} = \omega_{02} - (\omega_1 + \omega_2)$ for simplicity.

First of all we must calculate $A(t)$ in (27). This calculation is tedious even in the case of $n = 3$. The result is

$$A(t) = \exp(igtC)R(t)\exp(-igtC) = \frac{1}{2}\begin{pmatrix} a_{11} & a_{12} & a_{13} \\ a_{21} & a_{22} & a_{23} \\ a_{31} & a_{32} & a_{33} \end{pmatrix} \tag{50}$$

where

$$\begin{aligned}
a_{11} &= -\sin^2(\sqrt{2}gt)\cos(\epsilon t), \\
a_{12} &= \sqrt{2}\sin(\sqrt{2}gt)\sin(\epsilon t) - i\sqrt{2}\sin(\sqrt{2}gt)\cos(\sqrt{2}gt)\cos(\epsilon t), \\
a_{13} &= \left(1 + \cos^2(\sqrt{2}gt)\right)\cos(\epsilon t) + i2\cos(\sqrt{2}gt)\sin(\epsilon t), \\
a_{21} &= \sqrt{2}\sin(\sqrt{2}gt)\sin(\epsilon t) + i\sqrt{2}\sin(\sqrt{2}gt)\cos(\sqrt{2}gt)\cos(\epsilon t), \\
a_{22} &= 2\sin^2(\sqrt{2}gt)\cos(\epsilon t), \\
a_{23} &= -\sqrt{2}\sin(\sqrt{2}gt)\sin(\epsilon t) + i\sqrt{2}\sin(\sqrt{2}gt)\cos(\sqrt{2}gt)\cos(\epsilon t), \\
a_{31} &= \left(1 + \cos^2(\sqrt{2}gt)\right)\cos(\epsilon t) - i2\cos(\sqrt{2}gt)\sin(\epsilon t), \\
a_{32} &= -\sqrt{2}\sin(\sqrt{2}gt)\sin(\epsilon t) - i\sqrt{2}\sin(\sqrt{2}gt)\cos(\sqrt{2}gt)\cos(\epsilon t), \\
a_{33} &= -\sin^2(\sqrt{2}gt)\cos(\epsilon t).
\end{aligned}$$

Next we must calculate the Dyson series (28) with $A(t)$ above. To calculate all terms in (28) is of course impossible, so we calculate up to the next–leading term :

$$\phi(t) \approx \left[\mathbf{1} - ig\int_0^t A(s)ds\right]\phi(0) \tag{51}$$

with $\phi(0)$ being the ground state $\phi(0) = (1, 0, 0)^T$. By the way, it is convenient for us to calculate

$$\exp(-igtC)\phi(t) \approx \left[\exp(-igtC) - ig\int_0^t \exp(ig(s-t)C)R(s)\exp(-igsC)ds\right]\phi(0) \tag{52}$$

rather than (51) itself. The result is

$$\exp(-igtC)\phi(t) = (x_1(t), x_2(t), x_3(t))^T, \tag{53}$$

where

$$\begin{aligned}
x_1(t) = & \frac{1+\cos(\sqrt{2}gt)}{2} - \frac{ig}{4}\left(-2+\cos(\sqrt{2}gt)\right)\frac{\sin(\epsilon t)}{\epsilon} - \\
& \frac{ig}{8}\left\{\frac{\sin(\sqrt{2}gt)+\sin((\sqrt{2}g+\epsilon)t)}{2\sqrt{2}g+\epsilon} + \frac{\sin(\sqrt{2}gt)+\sin((\sqrt{2}g-\epsilon)t)}{2\sqrt{2}g-\epsilon}\right\} + \\
& \frac{g}{2}\sin(\frac{gt}{\sqrt{2}})\left\{\frac{\sin(\frac{gt}{\sqrt{2}})+\sin((\frac{g}{\sqrt{2}}+\epsilon)t)}{\sqrt{2}g+\epsilon} - \frac{\sin(\frac{gt}{\sqrt{2}})+\sin((\frac{g}{\sqrt{2}}-\epsilon)t)}{\sqrt{2}g-\epsilon}\right\},
\end{aligned}$$

$$\begin{aligned}
x_2(t) = & \frac{-i\sin(\sqrt{2}gt)}{\sqrt{2}} - \frac{\sqrt{2}g}{4}\sin(\sqrt{2}gt)\frac{\sin(\epsilon t)}{\epsilon} + \\
& \frac{i\sqrt{2}g}{4}\left\{\frac{\sin(\epsilon t)+\sin(\sqrt{2}gt)}{\sqrt{2}g+\epsilon} + \frac{\sin(\epsilon t)-\sin(\sqrt{2}gt)}{\sqrt{2}g-\epsilon}\right\} - \\
& \frac{\sqrt{2}g}{8}\left\{\frac{\cos((\sqrt{2}g+\epsilon)t)-\cos(\sqrt{2}gt)}{2\sqrt{2}g+\epsilon} + \frac{\cos((\sqrt{2}g-\epsilon)t)-\cos(\sqrt{2}gt)}{2\sqrt{2}g-\epsilon}\right\},
\end{aligned}$$

$$\begin{aligned}
x_3(t) = & \frac{-1+\cos(\sqrt{2}gt)}{2} - \frac{ig}{4}\left(2+\cos(\sqrt{2}gt)\right)\frac{\sin(\epsilon t)}{\epsilon} - \\
& \frac{ig}{8}\left\{\frac{\sin(\sqrt{2}gt)+\sin((\sqrt{2}g+\epsilon)t)}{2\sqrt{2}g+\epsilon} + \frac{\sin(\sqrt{2}gt)+\sin((\sqrt{2}g-\epsilon)t)}{2\sqrt{2}g-\epsilon}\right\} + \\
& \frac{g}{2}\cos(\frac{gt}{\sqrt{2}})\left\{\frac{-\cos(\frac{gt}{\sqrt{2}})+\cos((\frac{g}{\sqrt{2}}+\epsilon)t)}{\sqrt{2}g+\epsilon} - \frac{-\cos(\frac{gt}{\sqrt{2}})+\cos((\frac{g}{\sqrt{2}}-\epsilon)t)}{\sqrt{2}g-\epsilon}\right\}.
\end{aligned}$$

We leave the check of this calculation to the readers.

As a result we obtain the approximate solution (up to the next–leading) in the case of $n = 3$

$$\Psi(t) = \begin{pmatrix} 1 & & \\ & \mathrm{e}^{-i\omega_1 t} & \\ & & \mathrm{e}^{-i(\omega_1+\omega_2)t} \end{pmatrix} \begin{pmatrix} x_1(t) \\ x_2(t) \\ x_3(t) \end{pmatrix} = \begin{pmatrix} x_1(t) \\ \mathrm{e}^{-i\omega_1 t}x_2(t) \\ \mathrm{e}^{-i(\omega_1+\omega_2)t}x_3(t) \end{pmatrix} \tag{54}$$

with $x_1(t), x_2(t), x_3(t)$ above. This is our main result.

5 Discussion

In this paper we developed a general theory of the n level system by assuming the rotating wave approximation and gave an analytical solution under the "consistency condition". Moreover in the three level system we gave some approximate solution (up to the next–leading term), which may be enough because we are treating the weak coupling regime (g is small enough compared to the energy differences of the atom). To continue further calculations (higher order corrections) is not easy at the present.

Here we state our motivation once more. In Quantum Computation with three level system we must first of all construct or approximate all elements in $U(3)$ by making use of (a kind of) Rabi oscillations $\cdots$ a universality of one qudit theory. This is not an easy problem. In fact, in almost all papers in qudit theory this has not been mentioned as far as we know. Our paper is an attempt to this problem and we gave the approximate solutions (54). We need a furthermore study.

We list the equation in the three level system once more

$$i\frac{d}{dt}\begin{pmatrix}\Psi_1\\ \Psi_2\\ \Psi_3\end{pmatrix} = \begin{pmatrix} 0 & g\mathrm{e}^{i\omega_1 t} & g\mathrm{e}^{i\omega_{02}t}\\ g\mathrm{e}^{-i\omega_1 t} & \Delta_1 & g\mathrm{e}^{i\omega_2 t}\\ g\mathrm{e}^{-i\omega_{02}t} & g\mathrm{e}^{-i\omega_2 t} & \Delta_2\end{pmatrix}\begin{pmatrix}\Psi_1\\ \Psi_2\\ \Psi_3\end{pmatrix}. \tag{55}$$

and present

Problem Show a good method to solve (or to solve approximately) the equation above.

This problem seems to be very hard.

Moreover, study the general equation in the three level system (without the rotating wave approximation)

$$i\frac{d}{dt}\begin{pmatrix}\Psi_1\\ \Psi_2\\ \Psi_3\end{pmatrix} = \begin{pmatrix} 0 & g\cos(i\omega_1 t) & g\cos(i\omega_{02}t)\\ g\cos(-i\omega_1 t) & \Delta_1 & g\cos(i\omega_2 t)\\ g\cos(-i\omega_{02}t) & g\cos(-i\omega_2 t) & \Delta_2\end{pmatrix}\begin{pmatrix}\Psi_1\\ \Psi_2\\ \Psi_3\end{pmatrix}. \tag{56}$$

This is our next target !

Acknowledgment.

K. Fujii wishes to thank Akira Asada, Marco Frasca, Kunio Funahashi and Shin'ichi Nojiri for their helpful comments and suggestions.

References

[1] H-K. Lo, S. Popescu and T. Spiller (eds) : Introduction to Quantum Computation and Information, 1998, World Scientific.

[2] L. Allen and J. H. Eberly : Optical Resonance and Two–Level Atoms, Wiley, New York, 1975.

[3] P. Meystre and M. Sargent III : Elements of Quantum Optics, Springer–Verlag, 1990.

[4] S. M. Barnett and P. M. Radmore : Methods in Theoretical Quantum Optics, Oxford University Press, 1997.

[5] Claude Cohen–Tannoudji, J. Dupont–Roc and G. Grynberg : Atom–Photon Interactions ; Basic Processes and Applications, Wiley, New York, 1998.

[6] W. H. Zurek : Decoherence and the transition from quantum to classical–REVISITED, quant-ph/0306072.

[7] M. Frasca : Theory of dressed states in quantum optics, Phys. Rev. A 60(1999), 573, quant-ph/9811037.

[8] M. Frasca : Rabi flopping without resonance, Phys. Rev. A 64(2001), 033810.

[9] M. Frasca : Rabi oscillations and macroscopic quantum superposition states, Phys. Rev. A 66(2002), 023810, quant-ph/0111134.

[10] M. Frasca : A modern review of the two–level approximation, Ann. Phys, 306(2003), 193, quant-ph/0209056.

[11] M. Frasca : Perturbative results on localization for a driven two–level system, cond-mat/0303655.

[12] K. Fujii : Introduction to Grassmann Manifolds and Quantum Computation, J. Applied Math, 2(2002), 371, quant-ph/0103011.

[13] K. Fujii : Mathematical Structure of Rabi Oscillations in the Strong Coupling Regime, J. Phys. A 36(2003), 2109, quant-ph/0203135.

[14] K. Fujii : N–Level System Interacting with Single Radiation Mode and Multi Cat States of Schrödinger in the Strong Coupling Regime, quant-ph/0210166.

[15] K. Fujii : Two–Level System and Some Approximate Solutions in the Strong Coupling Regime, quant-ph/0301145.

[16] K. Fujii : How To Treat An N–Level System : A Proposal, quant-ph/0302050.

[17] J. C. A. Barata and W. F. Wreszinski : Strong Coupling Theory of Two Level Atoms in Periodic Fields, Phys. Rev. Lett. 84(2000), 2112, physics/9906029.

[18] A. Santana, J. M. Gomez Llorente and V. Delgado : Semiclassical dressed states of two-level quantum systems driven by nonresonant and/or strong laser fields, J. Phys. B 34(2001), 2371, quant-ph/0011015.

[19] K. Funahashi : Explicit Construction of Controlled–U and Unitary Transformation in Two–Qudit, quant-ph/0304078.

[20] Akira Asada : a private communication.